



# CLC1200

## Instrumentation Amplifier

### General Description

The CLC1200 is a low power, general purpose instrumentation amplifier with a gain range of 1 to 10,000. The CLC1200 is offered in 8-lead SOIC or DIP packages and requires only one external gain setting resistor making it smaller and easier to implement than discrete, 3-amp designs.

While consuming only 2.2mA of supply current, the CLC1200 offers a low 6.6nV/Hz input voltage noise and 0.2 $\mu$ Vpp noise from 0.1Hz to 10Hz.

The CLC1200 offers a low input offset voltage of  $\pm 125\mu$ V that only varies 0.1 $\mu$ V/ $^{\circ}$ C over it's operating temperature range of -40 $^{\circ}$ C to +85 $^{\circ}$ C. The CLC1200 also features 50ppm maximum nonlinearity. These features make it well suited for use in data acquisition systems.

### FEATURES


- $\pm 2.3$ V to  $\pm 18$ V supply voltage range
- Gain range of 1 to 10,000
- Gain set with one external resistor
- $\pm 125\mu$ V maximum input offset voltage
- 0.1 $\mu$ V/ $^{\circ}$ C input offset drift
- 700kHz bandwidth at G = 1
- 1.2V/ $\mu$ s slew rate
- 90dB minimum CMRR at G = 10
- 2.2mA maximum supply current
- 6.6nV/ $\sqrt{\text{Hz}}$  input voltage noise
- 70nV/ $\sqrt{\text{Hz}}$  output voltage noise
- 0.2 $\mu$ Vpp input noise (0.1Hz to 10Hz)
- DIP-8 or Pb-free SOIC-8

### APPLICATIONS

- Bridge amplifier
- Weigh scales
- Thermocouple amplifier
- ECG and medical instrumentation
- MRI (Magnetic Resonance Imaging)
- Patient monitors
- Transducer interface
- Data acquisition systems
- Strain gauge amplifier
- Industrial process controls


Ordering Information - [back page](#)

### Typical Application



Thermocouple Amplifier

### Competitive Plot



Absolute Maximum Ratings

Stresses beyond the limits listed below may cause permanent damage to the device. Exposure to any Absolute Maximum Rating condition for extended periods may affect device reliability and lifetime.

|  |                                    |
|--|------------------------------------|
| Supply Voltage .....                           | ±18V                               |
| Input Voltage Range .....                      | ±V <sub>S</sub> V                  |
| Differential Input Voltage (G = 1 to 10) ..... | 25V                                |
| Differential Input Voltage (G > 10) .....      | ≤ 0.05 (R <sub>G</sub> + 800) +1 V |
| Load Resistance (min) .....                    | 1Ω                                 |

Operating Conditions

|   |                             |
|---|-----------------------------|
| Supply Voltage Range .....              | ±2.3V to ±18V (4.6V to 36V) |
| Gain Range .....                        | 1 to 10,000                 |
| Operating Temperature Range .....       | -40°C to 85°C               |
| Junction Temperature .....              | 150°C                       |
| Storage Temperature Range.....          | -65°C to 150°C              |
| Lead Temperature (Soldering, 10s) ..... | 260°C                       |

Package Thermal Resistance

|   |         |
|---|---------|
| θ <sub>JA</sub> (DIP-8) .....   | 100°C/W |
| θ <sub>JA</sub> (SOIC-8) .....  | 150°C/W |
| Package thermal resistance (θ <sub>JA</sub> ), JEDEC standard, multi-layer test boards, still air |         |

ESD Protection

|  |       |
|--|-------|
| SOIC-8 (HBM) .....                     | 1.5kV |
| ESD Rating for HBM (Human Body Model). |       |

The product (or products) mentioned in this data sheet are no longer being manufactured and may not be ordered (OBS)

## Electrical Characteristics

$T_A = 25^\circ\text{C}$ ,  $V_S = \pm 15\text{V}$ ,  $R_L = 2\text{k}\Omega$  to GND; unless otherwise noted. Gain =  $1 + (49.4\text{k}/R_G)$ ; Total RTI Error =  $V_{OSI} + (V_{OSO}/G)$

| Symbol              | Parameter                               | Conditions   | Min                   | Typ   | Max                   | Units  |
|---------------------|---|--|-----------------------|-------|-----------------------|--------|
| Gain                |   |  |                       |       |                       |        |
|                     | Gain Range                              |  | 1                     |       | 10,000                |        |
|                     | Gain Error <sup>(1)</sup>               | G = 1, V <sub>OUT</sub> = ±10V                                     | -0.1                  |       | 0.1                   | %      |
|                     |   | G = 10, V <sub>OUT</sub> = ±10V                                    | -0.375                |       | 0.375                 | %      |
|                     |   | G = 100, V <sub>OUT</sub> = ±10V                                   | -0.375                |       | 0.375                 | %      |
|                     |   | G = 1,000, V <sub>OUT</sub> = ±10V                                 | -0.8                  |       | 0.8                   | %      |
|                     | Gain Nonlinearity                       | G = 1 - 100, V <sub>OUT</sub> = -10V to 10V, R <sub>L</sub> = 10kΩ |                       | 10    | 50                    | ppm    |
|                     |   | G = 1 - 100, V <sub>OUT</sub> = -10V to 10V, R <sub>L</sub> = 2kΩ  |                       | 10    | 95                    | ppm    |
|                     | Gain vs. Temperature                    | G = 1  |                       | <10   |                       | ppm/°C |
|                     |   | G > 1  |                       | <-50  |                       | ppm/°C |
|                     | Reference Gain Error <sup>(1)</sup>     | V <sub>S</sub> = ±16.5V  | -0.03                 |       | 0.03                  | %      |
| Voltage Offset      |   |  |                       |       |                       |        |
| V <sub>OSI</sub>    | Input Offset Voltage                    | V <sub>S</sub> = ±4.5V to ±16.5V                                   | -125                  |       | 125                   | μV     |
|                     | Average Temperature Coefficient         | V <sub>S</sub> = ±4.5V to ±16.5V                                   |                       | 0.1   |                       | μV/°C  |
| V <sub>OSO</sub>    | Output Offset Voltage                   | V <sub>S</sub> = ±4.5V to ±16.5V, G = 1                            | -1500                 | 200   | 1500                  | μV     |
|                     | Average Temperature Coefficient         | V <sub>S</sub> = ±4.5V to ±16.5V                                   |                       | 2.5   |                       | μV/°C  |
| PSR                 | Offset Referred to the Input vs. Supply | G = 1, V <sub>S</sub> = ±2.3V to ±18V                              | 80                    | 100   |                       | dB     |
|                     |   | G = 10, V <sub>S</sub> = ±2.3V to ±18V                             | 95                    | 120   |                       | dB     |
|                     |   | G = 100, V <sub>S</sub> = ±2.3V to ±18V                            | 110                   | 140   |                       | dB     |
|                     |   | G = 1000, V <sub>S</sub> = ±2.3V to ±18V                           | 110                   | 140   |                       | dB     |
| Input Current       |   |  |                       |       |                       |        |
| I <sub>B</sub>      | Input Bias Current                      | V <sub>S</sub> = ±16.5V  | -2                    | 0.5   | 2                     | nA     |
|                     | Average Temperature Coefficient         | V <sub>S</sub> = ±16.5V  |                       | 3     |                       | pA/°C  |
| I <sub>OS</sub>     | Input Offset Current                    | V <sub>S</sub> = ±16.5V  | -1                    |       | 1                     | nA     |
| Input               |   |  |                       |       |                       |        |
|                     | Input Impedance                         | Differential   |                       | 10, 2 |                       | GΩ, pF |
|                     |   | Common-Mode  |                       | 10, 2 |                       | GΩ, pF |
| IVR                 | Input Voltage Range <sup>(2)</sup>      | V <sub>S</sub> = ±4.5V, G = 1                                      | -V <sub>S</sub> + 1.9 |       | +V <sub>S</sub> - 1.2 | V      |
|                     |   | V <sub>S</sub> = ±16.5V, G = 1                                     | -V <sub>S</sub> + 1.9 |       | +V <sub>S</sub> - 1.4 | V      |
| CMRR                | Common-Mode Rejection Ratio             | G = 1, V <sub>S</sub> = ±16.5V                                     | 70                    | 90    |                       | dB     |
|                     |   | G = 10, V <sub>S</sub> = ±16.5V                                    | 90                    | 110   |                       | dB     |
|                     |   | G = 100, V <sub>S</sub> = ±16.5V                                   | 108                   | 130   |                       | dB     |
|                     |   | G = 1000, V <sub>S</sub> = ±16.5V                                  | 108                   | 130   |                       | dB     |
| Output              |   |  |                       |       |                       |        |
| V <sub>OUT</sub>    | Output Swing                            | V <sub>S</sub> = ±2.3V to ±4.5V                                    | -V <sub>S</sub> + 1.1 |       | +V <sub>S</sub> - 1.2 | V      |
|                     |   | V <sub>S</sub> = ±18V, G = 1                                       | -V <sub>S</sub> + 1.4 |       | +V <sub>S</sub> - 1.2 | V      |
| I <sub>SC</sub>     | Short Circuit Current                   |  |                       | ±20   |                       | mA     |
| Dynamic Performance |   |  |                       |       |                       |        |
| BW <sub>-3dB</sub>  | Small Signal -3dB Bandwidth             | G = 1  |                       | 700   |                       | kHz    |
|                     |   | G = 10   |                       | 400   |                       | kHz    |
|                     |   | G = 100  |                       | 100   |                       | kHz    |
|                     |   | G = 1000   |                       | 12    |                       | kHz    |
| SR                  | Slew Rate                               | G = 10, V <sub>S</sub> = ±15V                                      | 0.6                   | 1.2   |                       | V/μs   |
| t <sub>s</sub>      | Settling Time to 0.01%                  | 5V step, G = 1 to 100  |                       | 13    |                       | μs     |
|                     |   | 5V step, G = 1000  |                       | 110   |                       | μs     |

## Electrical Characteristics continued

$T_A = 25^\circ\text{C}$ ,  $V_S = \pm 15\text{V}$ ,  $R_L = 2\text{k}\Omega$  to GND; unless otherwise noted. Gain =  $1 + (49.4\text{k}/R_G)$ ; Total RTI Error =  $V_{OSI} + (V_{OSO}/G)$

| Symbol           | Parameter                  | Conditions                                    | Min                   | Typ | Max                   | Units            |
|------------------|----------------------------|---|-----------------------|-----|-----------------------|------------------|
| Noise            |                            |   |                       |     |                       |                  |
| e <sub>ni</sub>  | Input Voltage Noise        | 1kHz, G = 1000, V <sub>S</sub> = ±15V         |                       | 6.6 | 13                    | nV/√Hz           |
| e <sub>no</sub>  | Output Voltage Noise       | 1kHz, G = 1, V <sub>S</sub> = ±15V            |                       | 70  | 100                   | nV/√Hz           |
| e <sub>npp</sub> | Peak-to-Peak Noise (RTI)   | G = 1, 0.1Hz to 10Hz                          |                       | 5   |                       | μV <sub>pp</sub> |
|                  |                            | G = 10, 0.1Hz to 10Hz, V <sub>S</sub> = ±15V  |                       |     | 0.8                   | μV <sub>pp</sub> |
|                  |                            | G = 100, 0.1Hz to 10Hz, V <sub>S</sub> = ±15V |                       | 0.2 | 0.4                   | μV <sub>pp</sub> |
| i <sub>n</sub>   | Current Noise              | f = 1kHz                                      |                       | 100 |                       | fA/√Hz           |
| i <sub>npp</sub> | Peak-to-Peak Current Noise | 0.1Hz to 10Hz                                 |                       | 10  |                       | pA <sub>pp</sub> |
| Reference Input  |                            |   |                       |     |                       |                  |
| R <sub>IN</sub>  | Input Resistance           |   |                       | 20  |                       | kΩ               |
| I <sub>IN</sub>  | Input Current              | V <sub>S</sub> = ±16.5V                       |                       | 50  | 60                    | μA               |
|                  | Voltage Range              |   | -V <sub>S</sub> + 1.6 |     | +V <sub>S</sub> - 1.6 | V                |
|                  | Gain to Output             |   | 1±0.0001              |     |                       |                  |
| Power Supply     |                            |   |                       |     |                       |                  |
| V <sub>S</sub>   | Operating Range            |   | ±2.3                  |     | ±18                   | V                |
| I <sub>S</sub>   | Supply Current             | V <sub>S</sub> = ±16.5V                       |                       | 1.3 | 2.2                   | mA               |


### Notes:

1. Nominal reference voltage gain is 1.0
2. Input voltage range =  $\text{CMV} + (G V_{DIFF})/2$

The product (or products) mentioned in this data sheet are no longer being manufactured and may not be ordered (OBS)

CLC1200 Pin Configurations

SOIC-8, DIP-8



CLC1200 Pin Assignments

SOIC-8, DIP-8


| Pin No. | Pin Name | Description                                 |
|---------|----------|---|
| 1, 8    | $R_G$    | $R_G$ sets gain                             |
| 2       | $-IN$    | Negative input                              |
| 3       | $+IN$    | Positive input                              |
| 4       | $-V_S$   | Negative supply                             |
| 5       | REF      | Output is referred to the REF pin potential |
| 6       | OUT      | Output                                      |
| 7       | $+V_S$   | Positive supply                             |

The product (or products) mentioned in this data sheet are no longer being manufactured and may not be ordered (OBS)


## Typical Performance Characteristics

$T_A = 25^\circ\text{C}$ ,  $V_S = \pm 15\text{V}$ ,  $R_L = 2\text{k}\Omega$  to GND; unless otherwise noted.


Input Offset Distribution (typical)



Input Bias Current Distribution (typical)



Input Offset Current Distribution (typical)




The product (or products) mentioned in this data sheet are no longer being manufactured and may not be ordered (OBS)


## Typical Performance Characteristics

$T_A = 25^\circ\text{C}$ ,  $V_S = \pm 15\text{V}$ ,  $R_L = 2\text{k}\Omega$  to GND; unless otherwise noted.


Gain vs. Frequency




Output Voltage Swing vs.  $V_S$




Input Voltage Range vs.  $V_S$




Output Voltage Swing vs.  $R_L$



Large Signal Pulse Response ( $G = 1$ )




Large Signal Settling Time ( $G = 1$ )




## Typical Performance Characteristics

$T_A = 25^\circ\text{C}$ ,  $V_S = \pm 15\text{V}$ ,  $R_L = 2\text{k}\Omega$  to GND; unless otherwise noted.


Large Signal Pulse Response ( $G = 10$ )




Large Signal Settling Time ( $G = 10$ )




Large Signal Pulse Response ( $G = 100$ )




Large Signal Settling Time ( $G = 100$ )



Large Signal Pulse Response ( $G = 1000$ )



Large Signal Settling Time ( $G = 1000$ )







## Typical Performance Characteristics

$T_A = 25^\circ\text{C}$ ,  $V_S = \pm 15\text{V}$ ,  $R_L = 2\text{k}\Omega$  to GND; unless otherwise noted.


Small Signal Pulse Response ( $G = 1$ )




Small Signal Pulse Response ( $G = 10$ )



Small Signal Pulse Response ( $G = 100$ )



Small Signal Pulse Response ( $G = 1000$ )




The product (or products) mentioned in this data sheet are no longer being manufactured and may not be ordered (OBS)


## Typical Competitive Comparison Plots

$T_A = 25^\circ\text{C}$ ,  $V_S = \pm 15\text{V}$ ,  $R_L = 2\text{k}\Omega$ , Exar evaluation board; unless otherwise noted.


Frequency Response ( $G = 1$ )




Frequency Response ( $G = 10$ )




Frequency Response ( $G = 100$ )




Frequency Response ( $G = 1000$ )



Small Signal Pulse Response ( $G = 1$ )



Small Signal Pulse Response ( $G = 10$ )



## Application Information

### Basic Information

The CLC1200 is a monolithic instrumentation amplifier based on the classic three op amp solution, refer to the Functional Block Diagram shown in Figure 1. The CLC1200 produces a single-ended output referred to the REF pin potential.




Figure 1: Functional Block Diagram

The internal resistors are trimmed which allows the gain to be accurately adjusted with one external resistor  $R_G$ .

$$G = \frac{49.4k}{R_G} + 1; R_G = \frac{49.4k}{G - 1}$$

$R_G$  also determines the transconductance of the preamp stage. As  $R_G$  is reduced for larger gains, the transconductance increases to that of the input transistors. Producing the following advantages:

- Open-loop gain increases as the gain is increased, reducing gain related errors
- Gain-bandwidth increases as the gain is increased, optimizing frequency response
- Reduced input voltage noise which is determined by the collector current and base resistance of the input devices

### Gain Selection

The impedance between pins 1 and 8,  $R_G$ , sets the gain of the CLC1200. Table 1 shows the required standard table values of  $R_G$  for various calculated gains. For  $G = 1$ ,  $R_G = \infty$ .

| 1% $R_G$ ( $\Omega$ ) | Calculated Gain | 0.1% $R_G$ ( $\Omega$ ) | Calculated Gain |
|-----------------------|-----------------|-------------------------|-----------------|
| 49.9k                 | 1.990           | 49.3k                   | 2.002           |
| 12.4k                 | 4.984           | 12.4k                   | 4.984           |
| 5.49k                 | 9.998           | 5.49k                   | 9.998           |
| 2.61k                 | 19.93           | 2.61k                   | 19.93           |
| 1.00k                 | 50.40           | 1.01k                   | 49.91           |
| 499                   | 100.0           | 499                     | 100.0           |
| 249                   | 199.4           | 249                     | 199.4           |
| 100                   | 495.0           | 98.8                    | 501.0           |
| 49.9                  | 991.0           | 49.3                    | 1,003.0         |

Table 1: Recommended  $R_G$  Values

Follow these guidelines for improved performance:

- To maintain gain accuracy, use 0.1% to 1% resistors
- To minimize gain error, avoid high parasitic resistance in series with  $R_G$
- To minimize gain drift, use low TC resistors ( $<10\text{ppm}/^\circ\text{C}$ )

### Common Mode Rejection

The CLC1200 offers high CMRR. To achieve optimal CMRR performance:

- Connect the reference terminal (pin 5) to a low impedance source
- Minimize capacitive and resistive differences between the inputs

In many applications, shielded cables are used to minimize noise. Properly drive the shield for best CMRR performance over frequency. Figures 1 and 2 show active data guards that are configured to improve AC common-mode rejections. the capacitances of input cable shields are “bootstrapped” to minimize the capacitance mismatch between the inputs.




Figure 2: Common-mode Shield Driver




Figure 3: Differential Shield Driver

### Pressure Measurement Applications

The CLC1200 is especially suitable for higher resistance pressure sensors powered at lower voltages where small size and low power become more significant.

Figure 3 shows a  $3\text{k}\Omega$  pressure transducer bridge powered from 5V. In such a circuit, the bridge consumes only 1.7mA. Adding the CLC1200 and a buffered voltage divider allows the signal to be conditioned for only 3.8mA of total supply current.

Small size and low cost make the CLC1200 especially attractive for voltage output pressure transducers. Since it delivers low noise and drift, it will also serve applications such as diagnostic noninvasive blood pressure measurement.

### Medical ECG

The CLC1200 is perfect for ECG monitors because of its low current noise. A typical application is shown in Figure 4. The CLC1200's low power, low supply voltage requirements, and space-saving 8-lead SOIC package offerings make it an excellent choice for battery-powered data recorders.

Furthermore, the low bias currents and low current noise, coupled with the low voltage noise of the CLC1200, improve the dynamic range for better performance.

The value of capacitor C1 is chosen to maintain stability of the right leg drive loop. Proper safeguards, such as isolation, must be added to this circuit to protect the patient from possible harm.




Figure 4: Pressure Monitoring Circuits Operating on a Single 5V Supply




Figure 5: Typical Circuit for ECG Monitor Applications

## Grounding

The output voltage of the CLC1200 is developed with respect to the potential on the reference terminal (pin 8). Simply tie the REF pin to the appropriate “local ground” to resolve many grounding problems.

To isolate low level analog signals from a noisy digital environment, many data acquisition components have separate analog and digital ground pins. Use separate ground lines (analog and digital) to minimize current flow from sensitive areas to system ground. These ground returns must be tied together at some point, usually best at the ADC.

## Layout Considerations

General layout and supply bypassing play major roles in high frequency performance. Exar has evaluation boards to use as a guide for high frequency layout and as an aid in device testing and characterization. Follow the steps below as a basis for high frequency layout:

- Include 6.8 $\mu$ F and 0.1 $\mu$ F ceramic capacitors for power supply decoupling
- Place the 6.8 $\mu$ F capacitor within 0.75 inches of the power pin
- Place the 0.1 $\mu$ F capacitor within 0.1 inches of the power pin
- Remove the ground plane under and around the part, especially near the input and output pins to reduce parasitic capacitance
- Minimize all trace lengths to reduce series inductances

Refer to the evaluation board layouts below for more information.

## Evaluation Board Information

The following evaluation boards are available to aid in the testing and layout of these devices:

| Evaluation Board # | Products          |
|--------------------|-------------------|
| CEB024             | CLC1200 in SOIC-8 |

## Evaluation Board Schematics

Evaluation board schematics and layouts are shown in Figures 6-8. These evaluation boards are built for dual-supply operation. Follow these steps to use the board in a single-supply application:

1. Short  $-V_S$  to ground.
2. Use C3 and C4, if the  $-V_S$  pin of the amplifier is not directly connected to the ground plane.




Figure 6. CEB024 Schematic




Figure 7. CEB024 Top View





Figure 8. CEB024 Bottom View


## Mechanical Dimensions

### SOIC-8 Package



| 8 Pin SOICN JEDEC MS-012 Variation AA |                                    |     |      |  |     |       |
|---------------------------------------|------------------------------------|-----|------|--|-----|-------|
| SYMBOLS                               | DIMENSIONS IN MM<br>(Control Unit) |     |      | DIMENSIONS IN INCH<br>(Reference Unit) |     |       |
|                                       | MIN                                | NOM | MAX  | MIN                                    | NOM | MAX   |
| A                                     | 1.35                               | —   | 1.75 | 0.053                                  | —   | 0.069 |
| A1                                    | 0.10                               | —   | 0.25 | 0.004                                  | —   | 0.010 |
| A2                                    | 1.25                               | —   | 1.65 | 0.049                                  | —   | 0.065 |
| b                                     | 0.31                               | —   | 0.51 | 0.012                                  | —   | 0.020 |
| c                                     | 0.17                               | —   | 0.25 | 0.007                                  | —   | 0.010 |
| E                                     | 6.00 BSC                           |     |      | 0.236 BSC                              |     |       |
| E1                                    | 3.90 BSC                           |     |      | 0.154 BSC                              |     |       |
| e                                     | 1.27 BSC                           |     |      | 0.050 BSC                              |     |       |
| h                                     | 0.25                               | —   | 0.50 | 0.010                                  | —   | 0.020 |
| L1                                    | 0.40                               | —   | 1.27 | 0.016                                  | —   | 0.050 |
| L2                                    | 1.04 REF                           |     |      | 0.041 REF                              |     |       |
| R                                     | 0.07                               | —   | —    | 0.003                                  | —   | —     |
| R1                                    | 0.07                               | —   | —    | 0.003                                  | —   | —     |
| θ                                     | 0°                                 | —   | 8°   | 0°                                     | —   | 8°    |
| θ1                                    | 5°                                 | —   | 15°  | 5°                                     | —   | 15°   |
| θ2                                    | 0°                                 | —   | —    | 0°                                     | —   | —     |
| D                                     | 4.90 BSC                           |     |      | 0.193 BSC                              |     |       |
| N                                     | 8                                  |     |      | 8                                      |     |       |

### DIP-8 Package



| 8 Pin PDIP JEDEC MS-001 Variation BA |                                      |       |       |                                      |      |       |
|--------------------------------------|--------------------------------------|-------|-------|--------------------------------------|------|-------|
| SYMBOLS                              | DIMENSIONS IN INCH<br>(Control Unit) |       |       | DIMENSIONS IN MM<br>(Reference Unit) |      |       |
|                                      | MIN                                  | NOM   | MAX   | MIN                                  | NOM  | MAX   |
| A                                    | —                                    | —     | 0.210 | —                                    | —    | 5.33  |
| A1                                   | 0.015                                | —     | —     | 0.38                                 | —    | —     |
| A2                                   | 0.115                                | 0.130 | 0.195 | 2.92                                 | 3.30 | 4.95  |
| b                                    | 0.014                                | 0.018 | 0.022 | 0.36                                 | 0.46 | 0.56  |
| b2                                   | 0.045                                | 0.060 | 0.070 | 1.14                                 | 1.52 | 1.78  |
| c                                    | 0.008                                | 0.010 | 0.014 | 0.20                                 | 0.25 | 0.36  |
| D1                                   | 0.030                                | —     | 0.060 | 0.76                                 | —    | 1.52  |
| E                                    | 0.300                                | 0.310 | 0.325 | 7.62                                 | 7.87 | 8.26  |
| E1                                   | 0.240                                | 0.250 | 0.280 | 6.10                                 | 6.35 | 7.11  |
| e                                    | 0.100 BSC                            |       |       | 2.54 BSC                             |      |       |
| eA                                   | 0.300 BSC                            |       |       | 7.62 BSC                             |      |       |
| eB                                   | —                                    | —     | 0.430 | —                                    | —    | 10.92 |
| L                                    | 0.115                                | 0.130 | 0.150 | 2.92                                 | 3.30 | 3.81  |
| W                                    | 0.075 REF                            |       |       | 1.91 REF                             |      |       |
| R                                    | 0.030 BSC                            |       |       | 0.76 BSC                             |      |       |
| θ                                    | 4°                                   | 7°    | 10°   | 4°                                   | 7°   | 10°   |
| D                                    | 0.355                                | 0.365 | 0.400 | 9.02                                 | 9.27 | 10.16 |
| N                                    | 8                                    |       |       | 8                                    |      |       |

## Ordering Information

| Part Number    | Package          | Green | Operating Temperature Range | Packaging        |
|----------------|------------------|-------|-----------------------------|------------------|
| CLC1200ISO8X   | SOIC-8           | Yes   | -40°C to +85°C              | Tape & Reel      |
| CLC1200ISO8MTR | SOIC-8           | Yes   | -40°C to +85°C              | Mini Tape & Reel |
| CLC1200ISO8EVB | Evaluation Board | N/A   | N/A                         | N/A              |
| CLC1200IDP8    | DIP-8            | Yes   | -40°C to +85°C              | Rail             |

Moisture sensitivity level for all parts is MSL-1. Mini Tape and Reel contains 250 pieces.

## Revision History

| Revision         | Date       | Description  |
|------------------|------------|--|
| 2E (ECN 1513-02) | March 2015 | Reformat into Exar data sheet template. Updated PODs and thermal resistance numbers. Updated ordering information table to include MTR and EVB part numbers. Updated evaluation board top and bottom views to Rev b. Added schematic used for evaluation boards. |

The product (or products) mentioned in this data sheet are no longer being manufactured and may not be ordered (OBS)

For Further Assistance:

Email: [CustomerSupport@exar.com](mailto:CustomerSupport@exar.com) or [HPATechSupport@exar.com](mailto:HPATechSupport@exar.com)

Exar Technical Documentation: <http://www.exar.com/techdoc/>

### Exar Corporation Headquarters and Sales Offices

48760 Kato Road Tel.: +1 (510) 668-7000  
Fremont, CA 94538 - USA Fax: +1 (510) 668-7001



### NOTICE

EXAR Corporation reserves the right to make changes to the products contained in this publication in order to improve design, performance or reliability. EXAR Corporation assumes no responsibility for the use of any circuits described herein, conveys no license under any patent or other right, and makes no representation that the circuits are free of patent infringement. Charts and schedules contained here in are only for illustration purposes and may vary depending upon a user's specific application. While the information in this publication has been carefully checked; no responsibility, however, is assumed for inaccuracies.

EXAR Corporation does not recommend the use of any of its products in life support applications where the failure or malfunction of the product can reasonably be expected to cause failure of the life support system or to significantly affect its safety or effectiveness. Products are not authorized for use in such applications unless EXAR Corporation receives, in writing, assurances to its satisfaction that: (a) the risk of injury or damage has been minimized; (b) the user assumes all such risks; (c) potential liability of EXAR Corporation is adequately protected under the circumstances.

Reproduction, in part or whole, without the prior written consent of EXAR Corporation is prohibited.