



## General Description

The MxL541C is a low-power single-chip satellite receiver IC, featuring four L-band Full-Spectrum Capture<sup>®</sup> (FSC<sup>®</sup>) tuners and four demodulators that are compliant with DVB-S and DIRECTV legacy standards.

The MxL541C receives signals from the L-band RF inputs, each from 950 MHz to 2150 MHz, and demodulates four satellite channels to produce four independent serial TS outputs. All four TS outputs support two-wire, modes, or four-wire.

Each of the four TS output ports can carry a TS from any of the internal four DVB-S/DVB-S2/DIRECTV legacy demodulators.

The MxL541C communicates with satellite LNBS through on-chip DiSEqC and FSK modems.

All major functions are incorporated onto the device, including LNAs, channel filters, AGC, adaptive equalizers, PLLs, crystal load capacitors, and demodulators. The MxL541C enables simple, compact board designs with low-power consumption and reduced BOM costs.

The MxL541C is controlled via an I<sup>2</sup>C interface, and operates using 1.8V and 1.1V core supplies and an I/O supply of 3.3V. The MxL541C is available in a small 10 mm x 10 mm footprint 72-pin QFN package.

## Applications

- STBs
- Residential gateways
- SAT>IP multi-switch
- IP-LNB


## Features

- Ultra low power
- Symbol rates of:
  - 1 MSps to 45 MSps in DVB-S and DVB-S2 modes
  - 20 MSps to 30MSps in DIRECTV legacy mode
- DIRECTV full transponder loading compliant
- Broadcast wake-up
- Conversion from DIRECTV legacy packets to standard DVB-S/DVB-S2 TS packets
- Single-channel or Network Tuner mode
- Integrated LNAs
- Differential RF inputs
- Channel spectrum analysis data available through I<sup>2</sup>C
- On-chip programmable crystal load capacitors to reduce external components
- Coexistence with MoCA, LTE, and WiFi
- Automatic channel acquisition
- Auto-detection and auto-correction of spectral inversion
- Four serial TS output ports, configurable in two-wire, three-wire, or four-wire modes
- PID filtering and output TS multiplexing with 2:1 or 4:1 ratio in serial TS mode, or 4:1 ratio in parallel TS mode
- Unicable, EN50494:2007 and EN50607:2013 standards, and SWM single-cable LNB distribution
- DiSEqC 2.2 two-way LNB control interface and FSK modem
- I<sup>2</sup>C compatible interface

## Supported Standards

- DVB-S
- DVB-S2
- DIRECTV legacy standard

Block Diagram



Ordering Information

Marketing Part Number	Ordering Part Number	Package	Dimensions	Shipping
MxL541C	MxL541C-AK-T	SAWN QFN72	10 mm x 10 mm x 0.85 mm	Tray
MxL541C	MxL541C-AK-R	SAWN QFN72	10 mm x 10 mm x 0.85 mm	Tape and Reel



MaxLinear, Inc.

5966 La Place Court, Suite 100

Carlsbad, CA 92008

760.692.0711 p.

760.444.8598 f.

www.maxlinear.com

The content of this document is furnished for informational use only, is subject to change without notice, and should not be construed as a commitment by MaxLinear, Inc. MaxLinear, Inc. assumes no responsibility or liability for any errors or inaccuracies that may appear in the informational content contained in this guide. Complying with all applicable copyright laws is the responsibility of the user. Without limiting the rights under copyright, no part of this document may be reproduced into, stored in, or introduced into a retrieval system, or transmitted in any form or by any means (electronic, mechanical, photocopying, recording, or otherwise), or for any purpose, without the express written permission of MaxLinear, Inc.

Maxlinear, Inc. does not recommend the use of any of its products in life support applications where the failure or malfunction of the product can reasonably be expected to cause failure of the life support system or to significantly affect its safety or effectiveness. Products are not authorized for use in such applications unless MaxLinear, Inc. receives, in writing, assurances to its satisfaction that: (a) the risk of injury or damage has been minimized; (b) the user assumes all such risks; (c) potential liability of MaxLinear, Inc. is adequately protected under the circumstances.

MaxLinear, Inc. may have patents, patent applications, trademarks, copyrights, or other intellectual property rights covering subject matter in this document. Except as expressly provided in any written license agreement from MaxLinear, Inc., the furnishing of this document does not give you any license to these patents, trademarks, copyrights, or other intellectual property.

MaxLinear, the MaxLinear logo, and any MaxLinear trademarks, MxL, Full-Spectrum Capture, FSC, G.now, AirPHY and the MaxLinear logo are all on the products sold, are all trademarks of MaxLinear, Inc. or one of MaxLinear's subsidiaries in the U.S.A. and other countries. All rights reserved. Other company trademarks and product names appearing herein are the property of their respective owners.

© 2019 MaxLinear, Inc. All rights reserved.