



# **RS-485 Cable Lengths against Data Signaling Rate**

Application Note

## Revision History

| Document No. | Release Date  | Change Description   |
|--------------|---------------|--|
| 292ANR01     | July 15, 2022 | <b>Updated:</b> <ul style="list-style-type: none"><li>■ In "RS-485 Differential Output Voltages (<math>V_{OD}</math>)" figure, <math>50\Omega F</math> replaced with <math>50\Omega</math>.</li><li>■ In "RS-485 Cable Lengths" section. "10Mbps RS-485 driver" replaced with "1Mbps RS-485 driver".</li></ul> |
| 292ANR00     | April 6, 2022 | Initial release.   |

# Table of Contents

|                                    |          |
|------------------------------------|----------|
| <b>Introduction</b> .....          | <b>1</b> |
| <b>Related Documentation</b> ..... | <b>1</b> |
| <b>RS-485 Cable Lengths</b> .....  | <b>1</b> |

## List of Figures

|  |   |
|--|---|
| Figure 1: RS-485 Differential Output Voltages ( $V_{OD}$ ) .....                         | 1 |
| Figure 2: Cable Lengths versus Data Signaling Rate.....                                  | 2 |
| Figure 3: $t_{Rise}$ , $t_{Fall}$ and $t_{UI}$ Signal Transition Time Requirements ..... | 3 |
| Figure 4: Eye-Diagram at Driver Output.....  | 4 |
| Figure 5: Eye-Diagram at Receiver Input after 4000ft Cable @90Kbps.....                  | 4 |
| Figure 6: Eye-Diagram at Receiver Input after 4000ft Cable @2Mbps .....                  | 5 |
| Figure 7: Eye-Diagram at Receiver Input after 4000ft Cable @4Mbps .....                  | 5 |

## Introduction

This document describes how you can transmit an RS-485 signal without data loss.

When you interconnect an equipment with RS-485's drivers and receivers, you can get problems due to the cable characteristics, cable terminations, grounding arrangements, and RS-485 failsafe method.

## Related Documentation


- *TIA/EIA-485, Electrical Characteristics of Generators and Receivers for Use in Balanced Multipoint Systems. (known as RS-485 Standard).*
- *TIA/EIA-422-B, Electrical Characteristics of Balanced Voltage Digital Interface Circuits. (known as RS-422 Standard).*

## RS-485 Cable Lengths

Per the RS-485 standard, the minimum drive strength (or  $V_{OD}$ ) is 1.5V. If you need to use longer cable length, a RS-485 transceiver with a drive strength that exceed the RS-485 standard can offer better performance. MaxLinear offers RS-485/RS-422 transceivers with drive strength capability ( $V_{OD}$ ) above 1.5V with  $54\Omega$  load in parallel with 50pF.

In general, a higher drive strength helps to counter the DC-parasitic resistance of the interconnecting cable and support further communication distances at low data rates.


The following figure shows RS-485 differential output voltages.



**Figure 1: RS-485 Differential Output Voltages ( $V_{OD}$ )**

The maximum permissible length between a RS-485 driver and receiver is 4000ft (or 1200 meters). However, both cable quality and data rates impact this distance. As data rates increase, the signal is increasingly attenuated by the parasitic RC-filter created by the cable.

For more information about cable length versus data rate when you design RS-485, refer to the *TIE/EIA-422-B Annex-A guideline*. See also [Figure 2](#).




**Figure 2: Cable Lengths versus Data Signaling Rate**

This curve is based on empirical data that use a 24AWG unshielded twisted-pair copper conductor with a capacitance of 16pF/foot (or 52.4pF/meter) and terminated into a 100 $\Omega$  resistive load.

- The region A shows the maximum distance determined by the DC resistance of the cable. As the data signaling rate is reduced below 90Kbps, the maximum cable length is limited at 4000ft (or 1200 meters) by the assumed maximum allowable 66% signal loss at the receiver end.
- The region B shows the inverse relationship between the cable length and data rate. At a higher data signaling rates (from 90Kbps to 10Mbps), the cable length is decreased when the data rate is increased to maintain the rise-time and fall-time requirements. The maximum allowable distance between a driver and receiver is limit to about 50ft (or 15 meters) for signaling rate speeds above 10Mbps.

For a reliable communication, the maximum rise-time or fall-time of the driver should not exceed one third of the unit interval ( $t_{UI}$ ) at a given data rate. For example, a 1Mbps RS-485 driver has a unit interval ( $t_{UI}$ ) of 1000ns. The maximum rise-time ( $t_{Rise}$ ) and fall-time ( $t_{Fall}$ ) should not exceed one third of unit interval ( $t_{UI}$ ) ( $1000ns/3 = 333.33ns$ ).




**Figure 3:**  $t_{Rise}$ ,  $t_{Fall}$  and  $t_{UI}$  Signal Transition Time Requirements

Eye-diagrams show the attenuation affect caused by the transmission cable.


**Example 1**

In this example, a 4000ft of 24AWG-CAT5e cable is used between the driver output and the receiver input. **Figure 4** shows the input signal DI at 90Kbps as well as the output of the driver Y and Z, which shows an almost instantaneous rising and falling edge.

On the right-hand side after the 4000ft cable, the receiver sees rising and falling edges that look like RC-delay due to long cable pairs. However, the receiver can still successfully transmit the signal with no data errors because the receiver is seeing rising and the falling edges that fall within the 1/3 rule previously described. Note that the rise-time is about 584ns and the fall-time is about 619.25ns at the receiver input. Both are well under the 1/3 of unit interval requirement of 3703.67ns ( $11111/3 = 3703.67ns$ ).



**Figure 4: Eye-Diagram at Driver Output**




**Figure 5: Eye-Diagram at Receiver Input after 4000ft Cable @90Kbps**

## Example 2


In this example, the data rate is increased to 2Mbps and 4Mbps respectively. The cycle-to-cycle distortion is seen at the receiver RO output at 2Mbps and 4Mbps. The rise and fall times in both case exceed the 1/3 UI rule. Data loss at the receiver end is guaranteed to occur at these data rates over 1200m of cable.

The data signaling rate against the cable length graph (Figure 2 on page 2) indicates a maximum of 60m at 2Mbps and about 30m at 4Mbps for a successful transmission.

To operate the RS-485 driver at a maximum speed of 10Mbps and beyond, the maximum cable length between driver and receiver should be limited to a maximum of 15 meters (or 50 ft) of 24AWG cable.



**Figure 6: Eye-Diagram at Receiver Input after 4000ft Cable @2Mbps**



**Figure 7: Eye-Diagram at Receiver Input after 4000ft Cable @4Mbps**

In summary, the following tips help you to maintain a successful RS-485 link:

- Tip 1: Use the TIE/EIA-422-B graph as a guidelines to determine the maximum cable length between a RS-485 driver and a RS-485 receiver at a given data signaling rate.
- Tip 2: Obey the 1/3 rule (1/3 rise-time, 1/3 fall-time, and 1/3 bit-time) to guarantee no data loss. In a noisy environment, use the 1/4 rule (1/4 rise-time, 1/4 fall-time and 1/2 bit-time) for a better performance.
- Tip 3: Use a larger diameter cable to reduce the DC-parasitic loss and improve the signal performance over long distances. A 19-AWG cable perform better than a 24-AWG cable at the same length.
- Tip 4: Whenever possible, choose a RS-485's driver (or transmitter) with a higher  $V_{OD}$  than the standard RS-485 specification of 1.5V with load  $54\Omega$  parallel with  $50pF$ . A higher drive strength driver perform better than a standard drive strength RS-485 driver at the same cable length.



Corporate Headquarters:  
5966 La Place Court, Suite 100  
Carlsbad, CA 92008  
Tel.: +1 (760) 692-0711  
Fax: +1 (760) 444-8598

[www.maxlinear.com](http://www.maxlinear.com)

The content of this document is furnished for informational use only, is subject to change without notice, and should not be construed as a commitment by MaxLinear, Inc. MaxLinear, Inc. assumes no responsibility or liability for any errors or inaccuracies that may appear in the informational content contained in this guide. Complying with all applicable copyright laws is the responsibility of the user. Without limiting the rights under copyright, no part of this document may be reproduced into, stored in, or introduced into a retrieval system, or transmitted in any form or by any means (electronic, mechanical, photocopying, recording, or otherwise), or for any purpose, without the express written permission of MaxLinear, Inc.

MaxLinear, Inc. does not recommend the use of any of its products in life support applications where the failure or malfunction of the product can reasonably be expected to cause failure of the life support system or to significantly affect its safety or effectiveness. Products are not authorized for use in such applications unless MaxLinear, Inc. receives, in writing, assurances to its satisfaction that: (a) the risk of injury or damage has been minimized; (b) the user assumes all such risks; (c) potential liability of MaxLinear, Inc. is adequately protected under the circumstances.

MaxLinear, Inc. may have patents, patent applications, trademarks, copyrights, or other intellectual property rights covering subject matter in this document. Except as expressly provided in any written license agreement from MaxLinear, Inc., the furnishing of this document does not give you any license to these patents, trademarks, copyrights, or other intellectual property.

MaxLinear, the MaxLinear logo, any MaxLinear trademarks (MxL, Full-Spectrum Capture, FSC, G.now, AirPHY, Puma, and AnyWAN), and the MaxLinear logo on the products sold are all property of MaxLinear, Inc. or one of MaxLinear's subsidiaries in the U.S.A. and other countries. All rights reserved. \*Other company trademarks and product names appearing herein are the property of their respective owners.